

MIDI interface [MESA, ROADSTER] v2.2

EM Custom

Instruction manual

1. PROGRAM CHANGE switching

MUTE	REVERB	SOLO	LOOP	CH1	CH2	CH3	CH4
				PC message (0 - 127)			
○	○	○	○	64	80	96	112
○	○	○	●	65	81	97	113
○	○	●	○	66	82	98	114
○	○	●	●	67	83	99	115
○	●	○	○	68	84	100	116
○	●	○	●	69	85	101	117
○	●	●	○	70	86	102	118
○	●	●	●	71	87	103	119
●	○	○	○	72	88	104	120
●	○	○	●	73	89	105	121
●	○	●	○	74	90	106	122
●	○	●	●	75	91	107	123
●	●	○	○	76	92	108	124
●	●	○	●	77	93	109	125
●	●	●	○	78	94	110	126
●	●	●	●	79	95	111	127

2. CONTROL CHANGE switching

Function	controller number (0 - 127)	Value (1 - 127)	
		0 - 63	64 - 127
Channel 1	76	-	●
Channel 2	77	-	●
Channel 3	78	-	●
Channel 4	79	-	●
LOOP	80	○	●
SOLO	81	○	●
MUTE	82	○	●
REVERB	83	○	●